

miro-Adapter MC1

The miro-Adapter and the supplied video cable connect your miro monitor to any Macintosh video card and any Macintosh onboard video card.

The miro-Adapter has six DIP switches: DIP switches 1,2,3 select the resolution of your monitor. Switches 4,5,6 adjust your monitor to the synchronization mode of your video card.

All switches are factory-set to «OFF».



Selecting the resolution

To set the resolution, refer to the table:

Resolution	1	2	3
512 x 384	on	off	on
640 x 480	on	off	off
832 x 624	off	off	on
1024 x 768	off	on	off
1152 x 870	on	on	on
PAL	off	on	on
NTSC	on	on	off



A wrong switch position can damage your monitor seriously. If you are in doubt about the correct setting, consult the manual of your monitor.

Selecting the synchronization mode

To adjust your monitor to the synchronization mode of your video card, refer to the table:

	4	5	6
Sync In Green	off	off	off
Sep. Sync	on	on	off
C Sync	off	off	on

If you are in doubt about the synchronization mode of your monitor or about the setting of the resolution, refer to the documentation of your video card or consult your dealer.